

# Solution Kits

For EchoGuard® and EchoGuard CR

Typical Deployments.



Accelerated.



Get more out of EchoGuard and EchoGuard CR.

Quick Start Kit. Everything you need to start integration and testing.

Rapid Deployment Kit. One Pelican case contains everything required for 12+ hours of mission-critical radar performance.

Lightweight Deployment Kit. A sibling to the rapid deployment kit, the LDK packs everything into a backpack weighing <20

Tower Mounting Kit. Three sizes to configure and operate 2 km hemispherical ground and/or airspace surveillance.















# Solution Kits

For EchoGuard and EchoGuard CR

## Rapid Deployment Kit

- + Compact tripod with pan/tilt head and quick release for rapid & precise positioning
- + Wired connectivity w CAT6 outdoor cables & IP67 connectors
- + Molle deployment pouch (hold operating battery)
- + Radar mounting bracket with red dot aiming sight
- + Pelican 1620 case with storage for:
  - \* 2x BB-2590 7.5 Ah Li-ion batteries
  - \* Rugged computer or tablet



**Ordering Information** 

**EchoGuard RDK** 

700-0017-001-100

W/out red dot

700-0017-002-100

#### **Quick Start Kit**

- +8' interface cable
- + Quick release radar mounting bracket
- + Radar absorbing desktop foam for indoor testing and configuration
- + 24V/3A AC/DC wall supply, 5.5 mm barrel connector




**Ordering Information** 


**EchoGuard QSK** 

710-0002-203-100

### **Tower Mounting Kit**

- +1km sUAS radial coverage
- + Modular system includes arm brackets and pole adapter
- + Pole diameters from 65 225+ mm
- + Arm brackets include swivel for customized orientations





E Rada

Ordering Information

**Small** (65-110mm)

700-0016-001-100

**Medium** (80-150mm)

700-0016-002-100

Large (210-225mm)

700-0016-003-100

# **Lightweight Deployment Kit**

- + All componets fit in pack weighing < 20 lbs. (<9 kg)
- + Compact tripod with quick release radar mounting bracket
- + Versatile 3-zip closure pack holds all equipment
- + Ships in rugged Nanuk case



**Ordering Information** 

**EchoGuard LDK** 

700028-000-100